


KAOSS PAD KP3+ System Firmware Update


Update Procedures (for Windows users)

-  This updater is compatible with Windows 7 or later. Do not try to run it with Windows 98/Me/2000/XP/Vista.
 -  Do not operate the KAOSS PAD KP3+ or the computer during the update process.
1. Set the Power Switch of the KAOSS PAD KP3+ to the [STANDBY] position, and connect to a computer using a USB cable. Plug the connector of the included AC adapter firmly into the [DC 9V] input. Then connect the AC adapter to an AC power outlet.
 2. Unzip the "[KP3PlusUpdater_0104.zip](#)".
-  Extract all the files in the zip file before proceeding to step 3. The updater may not be able to find necessary files if they were not unzipped.
3. Execute one of the "[KP3PlusUpdater64.exe](#) (for 64bit)" or "[KP3PlusUpdater.exe](#) (for 32bit)" by double-clicking on it. The following window will appear:



-  Don't click on the screen yet!
4. Hold down the SAMPLE BANK [C], [D], and [SAMPLING] buttons, and then turn on the power of the KAOSS PAD KP3+. (The display of the KAOSS PAD KP3+ will indicate "IPL".) Please ignore the warning messages that may appear on the taskbar.


5. The following window will appear. Press the [OK] button.




6. During the installation, the following message may appear. Press the [Install] button, and proceed to the next step.



7. When the driver installation is completed, the following window will appear. Press the [Update] button to start the update procedure. (This window corresponds to the KAOSS PAD KP3+ system version 1.02.).




- ⚠ If the following message is shown, the system firmware is already up to date, and no update is necessary. If so, you can quit the KAOSS PAD KP3+ Updater.




- ⚠ If a "Product ID Error" message is shown after pressing the [Update] button, the updater is likely not for the product you are trying to update. Please check again to be sure you are using the right updater for your product.

8. The following window will appear during the update process.




 Do not disconnect the KAOSS PAD KP3+ from the computer or turn off the power to the KAOSS PAD KP3+ during the update process. Note that the whole process will take several minutes to complete.


9. After the update is finished, the following window will appear. Press the [OK] button.



10. The following window will appear. Disconnect a USB cable, and press the [OK] button to uninstall the driver.




11. After the uninstall process, the following window will appear. Press the [OK] button.



12. This concludes the entire update procedure. Quit the KA OSS PAD KP3+ Updater, and reboot the KA OSS PAD KP3+.

Update Procedures (for Mac users)

- ⚠ This updater is compatible with Mac OS X 10.9 or later.
 - ⚠ Do not operate the KAOSS PAD KP3+ or the computer during the update process.
1. Set the Power Switch of the KAOSS PAD KP3+ to the [STANDBY] position, and connect to a computer using a USB cable. Plug the connector of the included AC adapter firmly into the [DC 9V] input. Then connect the AC adapter to an AC power outlet.
 2. Quit other applications and the settings. Mount the "[KP3PlusUpdater_0104.zip](#)" by double-clicking on it, and run the "[KAOSS PAD KP3+ Updater](#)" in the disk image by double-clicking on it. The following window will appear.



3. Hold down the SAMPLE BANK [C], [D], and [SAMPLING] buttons, and then turn on the power of the KAOSS PAD KP3+. (The display of the KAOSS PAD KP3+ will indicate "IPL".)
The message in the window will change as follows.




- ⚠ If the following message is shown, the system firmware is already up to date, and no update is necessary. If so, you can quit the KAOSS PAD KP3+ Updater.



4. Press the [Update] button. The update process will start.



-  Do not disconnect the KAOSS PAD KP3+ from the computer or turn off the power to the KAOSS PAD KP3+ during the update process. Note that the whole process will take several minutes to complete.
5. The following message will be shown when the update has successfully completed. Quit the KAOSS PAD KP3+ Updater, and reboot the KAOSS PAD KP3+.



About the KAOSS PAD KP3+ System Version 1.04

- Fixed a bug on external MIDI clock sync feature.