

electribe sampler Ver 1.15 Release Information


Changes in Ver 1.15 from Ver 1.14

Bug fix

- Reduced noise generated under all the following conditions are met:
 - Global parameter "AUDIO IN THRU" is "On".
 - Global parameter "POWER SAVE MODE" is "Enabled".

What you will need

- Memory card supported by electribe sampler
- Computer with memory card adapter
- AC adapter KA350 or six AA batteries

 **Make sure the batteries are brand new if using alkaline or fully charged if using NiMH batteries.**

Updating the software

- Prepare a memory card that has been formatted by electribe sampler.
- Insert the memory card into your card reader, and connect it to your computer.
- Extract electribe_sampler_xxxx.zip.
- Copy "SYSTEM.VSB" into the [System] folder under the [KORG][electribe sampler] folder on the memory card.
- Insert the memory card containing the new system file into your electribe, and turn on the power.
- Select "SOFTWARE UPDATE" from the DATA UTILITY menu.

```
Data Util 26/27  EDIT  █ █ █ █  
DATA UTILITY  
press [ Enter ]
```

```
Data Util 13/13  EDIT  █ █ █ █  
SOFTWARE UPDATE  
press [ Enter ]
```

- Press Menu/Enter. Current version and new version will appear. Press Menu/Enter button.

```

Data Util 13/13  EDIT  ■■■
SOFTWARE UPDATE
Now Version : 1.14
Next Version : 1.15
press [ Enter ]

```

- A confirmation message will appear. Press Menu/Enter button to begin the update operation.

```

Data Util 13/13  EDIT  ■■■
SOFTWARE UPDATE
Are You Sure ?
press [ Enter ]

```

 **Do not turn off electribe sampler while update is in progress.**

- electribe sampler will display the following screen when update is complete.

```

Data Util 13/13  EDIT  ■■■
SOFTWARE UPDATE
OK. Please Reboot.

```

- Long push the power button. electribe sampler will now turn off. The system has been updated.