

MIDI Implementation Chart

Function...		Transmitted	Recognized	Remarks
Basic Channel	Default	1–16	1–16	Memorized
	Changed	1–16	1–16	
Mode	Default	X	3	
	Messages	X	X	
	Altered	*****	*****	
Note Number		X	0–127	
	True voice	X	12–127	
Velocity	Note On	X	O 9n, V=1–127	
	Note Off	X	X	
After Touch	Key's	X	X	
	Channel	X	X	
Pitch Bend		X	O	
Control Change	5	X	O	Portamento Time
	65	X	O	Portamento
	69	X	O	Hold 2 *3
	120	X	O	All Sound Off *1
	121	X	O	Reset All Controllers
Program Change		X	X	
	True Number	*****	*****	
System Exclusive		O	O	*2
System Common	Song Position	X	X	
	Song Select	X	X	
	Tune Request	X	X	
System Real Time	Clock	X	X	
	Commands	X	X	
Aux Meassages	Local On/Off	X	X	
	All Notes Off	X	O (123–127)	
	Active Sensing	X	O	
	System Reset	X	X	
Notes				
*1: Treated as All Notes Off.				
*2: In addition to messages specifically for this device, Device Inquiry is also supported.				
*3: Works as an interval latch. For details, refer to the ARP 2600 FS Owner's Manual.				

Mode 1: Omni On, Poly
Mode 3: Omni Off, Poly

Mode 2: Omni On, Mono
Mode 4: Omni Off, Mono

O: Yes
X: No

Consult your local Korg distributor for more information on MIDI implementation.