

# minilogue System Firmware Update

## Update Procedures


- ⚠ This updater is compatible with Windows 7 SP1 or later. Do not try to run it with Windows 98/Me/2000/XP/Vista.
- ⚠ The latest "KORG USB-MIDI Driver" needs to be installed before the update.  
If the driver installed on your computer is older than latest version, install the latest version of the driver before starting the update. (<http://www.korg.com>)
- ⚠ Do not operate the minilogue or the computer during the update process.
- ⚠ Close all other applications before running the updater.
- ⚠ After updating to, do not downgrade to a previous system version. The operation of a downgraded unit will not be guaranteed.

1. Unzip the "minilogue\_Updater\_???\_win.zip". (??? is version number)


- ⚠ Extract all the files in the zip file before proceeding to step 3. The updater may not be able to find necessary files if they were not unzipped.

## Update System Firmware


2. Turn on the power of the minilogue while holding the [6] and [8] buttons. This will put it in "Update Mode".




3. Execute the "kmupdate.exe". The following window will appear.



4. Push the Update button in the window to start the process.



- ⚠ The updater cannot recognize the minilogue if step 2 and step 3 are not done in the right order.
  - ⚠ Do not disconnect the minilogue from the computer or turn off the power to the minilogue during the update process. Note that the whole process will take several minutes to complete.
  - ⚠ If "Already the latest system" message is shown, the system firmware is already up to date. Please skip to step 5.
5. After the update is finished, quit the System Updater, and disconnect the minilogue from the computer and turn the power off and on.



6. Depending on the version, voice update mode may run. In this case please wait until it completes and "Please Reboot" is displayed and reboot again.
7. Turn on the power of the minilogue while holding the [8] buttons. You can confirm the current system version.